


# INSTALLATION MANUAL

## TIS AIR ADS 2-3 RELAYS

### RELAY MODULE WITH WI-FI COMPATIBILITY












Model: ADS-2R-2Z, ADS-3R-3Z





## PRODUCT INFORMATION

The ADS Relay is a Wi-Fi module with 2-3 relays. It can be used to control lights and shutters and can connect to the Internet for remote control via the TIS app. It includes 2-3 dry inputs that can be linked to any mechanical wall switch or 3<sup>rd</sup>-party sensor.

### PRODUCT SPECIFICATIONS

	<b>Power supply</b>	Input Voltage	110-230 VAC 50/60 Hz
		Output Power	3W / 12V
		Protection	Built in Protection fuse
		Current consumption	10-20 mA / 12 V DC
	<b>Output</b>	Number of relays	2 - 3 (refer to Model number)
		Nominal voltage	110 / 230 V AC 50/60 Hz
		Nominal current per channel	8 A / 230 VAC
	<b>Output switching current</b>	Max switching current	10A/230 VAC Resistive
			6A/230 VAC florescent
		Max Continues current	8A/230 VAC
		Max. switching Voltage	277VAC / 30VDC
	<b>Output service life</b>	Mechanical Endurance	> 10,000,000 OPS
	<b>Output switching times</b>	Operating time	8 mS (at nomi. Volt)
		Releasing time	5 mS (at nomi. Volt)
		Max. operating frequency	25 cycle/min
	<b>TIS AIR</b>	Number of devices on 1 line	Max. 64
		Bus voltage	12-32 V DC
		Current consumption	<60 mA / 24 V DC
	<b>Reaction time</b>		approx. 30ms
	<b>Mounting</b>	Free locate	Can be installed anywhere
	<b>Operating and display elements</b>	Digital inputs	2 dry inputs for control ...
		TIS AIR	TIS Protocol messages and commands
		PRG Button with LED	Programming button and status LED.
		Upgrading	By WIFI Connection
	<b>Dimensions</b>	(Width × Length × Height)	50mm × 35mm × 50mm
	<b>Housing</b>	Materials	PC fire proof
		Internal Parts color	White
		IP rating	IP 50





### Read Instructions

We recommend that you read this Instruction Manual before installation.



### Mounting Location

Install in a dry, indoor area with a suitable temperature and humidity range.



### Safety instructions

Electrical equipment should only be installed and fitted by electrically skilled persons.

Failure to observe the instructions may cause damage to the device and other hazards.

These instructions are an integral part of the product and must remain with the end customer.



### Electrical Wires

The recommended wire size for light channels is 2.5mm, for the Line, Neutral, and Load cables. The installer should consider the total current consumption when selecting the wires.



### Warranty

There is a two-year warranty provided by law. The hologram warranty seal and product serial number are available on each device.



### Programming

This device can be tested and programmed manually. Advanced programming requires knowledge of the TIS Device Search software and instruction in the TIS advanced training courses.



### Simple Installation

it fits on most junction box sizes or can be located anywhere.






## INSTALLATION STEPS

1»


Turn off the power at the main circuit breaker to turn off voltage supply to the switch.



**WARNING! HIGH VOLTAGE**


2»

Remove the switch cover. Unscrew and pull the wall switch out. Take the wires out of the load and line.



3»

Find a total of 3-5 wires (3 wires if 1 channel, 4 wires if 2 channels, 5 wires if 3 channels).






## INSTALLATION STEPS


4»

Turn on the power at the main power breaker, and carefully identify the live wire using a voltage tester, and find the neutral wire.




5»

Turn off the main power breaker.




6»

Attach the neutral and live wires to the N & L terminals, respectively.



7»

Attach the switch1, 2, & 3 wires to the S1, S2, & S3 terminals, respectively.








## INSTALLATION STEPS



8»

Connect the 3 Dry inputs wires to the wall switch or any 3<sup>rd</sup> party sensor.



9»

Turn on the breaker. The module should turn on accordingly.




### SERVER LINKING

In order for a project to be fully linked to the TIS server, server configuration must be enabled in just 1 product within that project.


If you have already done that with any other panel, just ignore these steps and proceed to configuration steps.

To do the server linking, complete the following steps:

- 1» In the TIS App, go to Settings ► Connect Server, and follow the steps by entering your SSID password.




- 2» On the module, press and hold the PRG button for 6 seconds. The PRG LED will start blinking.




### SERVER LINKING

- 3» On the TIS app, press Search and wait for a few seconds. The panel will link to your Wi-Fi, and the PRG button will turn blue.




- 4» Select your server option and 4-digit password. Then, press Save.




### CONFIGURATION STEPS


**1** In the TIS App, go to the Settings ► AIR Device Configuration, and follow the steps by entering your SSID password.



**2** On the module, press and hold the PRG button for 6 seconds. The PRG LED will start blinking.




**3** On the TIS app, press Search and wait for a few seconds. The module will link to your Wi-Fi, and the PRG LED will turn blue.






### CONFIGURATION STEPS


**4** » Select the Relay type (Lights, Curtain).



**5** » Select the room; then, select channel names and icons.




1




2

**6** » Go to the configured room's page and start controlling.



1



2




### PAIRING (MANUAL PROGRAMMING)

To pair the TIS ADS module with any TIS wall panel buttons, do the following:


1»

Short press on the PRG button five times in a row until the PRG LED starts to blink every 2 seconds.





2»

Go to any other wall panel and short press on any lighting button.



3»

Test by pressing on the wall panel's ON/OFF button. The module relay should respond by turning ON and OFF accordingly.



### PAIRING (MANUAL PROGRAMMING)


**4»** The same procedure must be followed to program other relay channels. The only exception is that you must press the PRG button six and seven times for channels 2 and 3 accordingly. The following table displays method info in detail.

METHOD	RESPONSE
Channel 1: 5 Short presses on the PRG button	PRG LED blinks once every 2 seconds
Channel 2: 6 Short presses on the PRG button	PRG LED blinks twice every 2 seconds
Channel 3: 7 Short presses on the PRG button	PRG LED blinks three times every 2 seconds

### USER OPERATION

**»** Use your mobile app or smart wall switches to control lights ON/OFF.

**Notice:** Wall switches need to be configured with this module's dry inputs beforehand.





## TROUBLESHOOTING



**PRG button blinks purple color rapidly**

**Reason:** The panel address conflicts with another device in the TIS network. You need to press and hold the PRG button for 6 seconds so that the module can get a new address.



**Device's PRG LED is RED**

**Reason:** The device is not connected to Wi-Fi.



**Device can't link to Wi-Fi router**

**Reason 1:** The device is too far from the WiFi router.

**Reason 2:** The SSID or password is not correct.

**Reason 3:** Some setting in the WIFI router is preventing new devices from being added.



**Other wall panels can't pair with the device**

**Reason 1:** Other panel connections are not linked to the same Wi-Fi network.

**Reason 2:** The manual programming function is disabled in the device (default is enabled).



**Other wall panels can't control the device channels**

**Reason 1:** Other panel connections are not linked to the same Wi-Fi network.

**Reason 2:** The programming address is wrong.