

60mm      60mm      60mm      60mm      60mm      60mm

### BASIC INFORMATION

This smart touch panel is a direct replacement for your traditional built-in switches. Mount with the use of existing in-wall back boxes to easily upgrade the lighting system of your property. This Zigbee-powered switch provides you with new ways to control your home limitlessly even when you are not home.

**1**

### WARNINGS & SAFETY INSTRUCTIONS

**The following must be read, kept, and observed before installation:**

- Mount in a neat and dry location with a suitable temperature and humidity level
- Avoid mounting near strong signal sources such as microwave oven that may cause signal interruption resulted in abnormal operation of the device
- Keep out of the reach of children, and away from water, damp or hot environment
- Do not attempt to open, service, or modify this device

**2**

### MOUNTING THE DEVICE

Use two screws to fit this panel into standard junction boxes

- Turn off the power at the main circuit breaker
- Remove the switch cover. Unscrew and pull the wall switch out. Then, take the wires out of the load and line
- Connect the load wires to S1, S2, S3, and the live wire to the L terminal
- Insert the switch and the wires in the box and fix using 2 screws
- Mount the top cover as shown in the picture
- Turn on the power supply

**3**

### CONFIGURATION

- Download the App  
Search for TIS Control & download the app
- Set up your hub (if not already set in the application)
- Go to Settings, and enter the default username and password  
Username: user  
Password: tis777
- Go to the TIS-BEE configuration button, and follow the instructions

**4**

80 mm

### 5 Add the Device

In the TIS-Bee configuration, press Add Device. Then, follow the instructions to add the device using the 2 available methods

a. Scan QR Method

b. Search Method

Select whichever method you prefer, and follow the instructions on the app

**7**

### TECHNICAL SPECIFICATIONS

**Communication Protocol**  
Zigbee® 3.0 Network

**Rated Voltage**  
110-230 V AC

**Operating & display elements**  
4 touch buttons with RGB backlit

**Dimensions**  
85mm x 109mm x 42mm

**Material**  
PC fire-proof/ glass in front

**8**

### RESET TO FACTORY DEFAULT

Press and hold any button for 6 seconds.

**9**


### TROUBLESHOOTING

Problem	Possible Cause	Solution
Unable to pair	Switch not in pairing mode	Reset the Switch to factory mode
	Switch is away from the hub, or there are obstacles	Move Switch closer to the hub
	Switch is connected to another hub network	Reset the Switch to factory default

**10**

## TIS BEE User Manual

Dione Light Switch



Product specifications, size, shape, and prices are subject to change without notice, and actual product appearance may differ from that depicted on the packaging.

**TIS TIS CONTROL LIMITED**  
 RM 1502-p9 Easey Comm Bldg 253-261  
 Hennessy Rd Wanchai, Hong Kong  
[www.tiscontrol.com](http://www.tiscontrol.com)



Please read the user manual carefully before operation